### SFKHUM/SFNHUM SWITCHES SPECIFICATIONS SFKHUM/SFNHUM 觸 壓 式 製 品 規 格 書

98.09.18

1.General 一般事項

1.1 Scope : This specification covers the requirements for single key switches which have no keytop. (TACT SWITCHES:MECHANICAL CONTACT).

適用範圍: 本規格書適用於不含鍵帽之單鍵開關(觸壓式開關:機械式接點)

- 1.2 Operating Temperature Range -20~+70℃ (normal humidity ☆normal press.)使用溫度範圍: -20~+70℃ (常濕常壓條件下)
- 1.3 Storage Temperature Range -30~+80°C (normal humidity ☆normal press.) 存放溫度範圍 :-30~+80°C (常濕常壓條件下)
- 1.4 Test conditions : The standard test conditions shall be  $5\sim35^{\circ}\text{C}$  in temperature ,  $45\sim85\%$  RH and  $860\sim1060$ mbar in atmospheric pressure. Should any doubt arise in judgement, tests shall be conducted at  $20\pm2^{\circ}\text{C}$  ,  $65\pm5\%$  RH. and  $860\sim1060$ mbar.
- 試 驗 狀 態:若無特別規定限制,則以溫度 5~35℃,相對濕度 45~85%,氣壓 860~1060mbar 之標準 狀態測之。但對此標準狀態之測定值發生判定疑問或有特別要求則以基準狀態(溫度 20±2℃ 相對濕度 65±5%.氣壓 860~1060mbar)為準測定
- 2.Appearance, construction and dimensions. 外觀.構造.尺寸
  - 2.1 Appearance: There shall be no defects that affect the serviceability of the product. 不得有影響製品機能之缺陷.
  - 2.2 Construction dimensions: Shall conform to the assembly drawings.構造及尺寸:必須與組立圖符合.
- 3. Type of actuation: Tactile feedback

動作型式:有觸感之反饋

- 4.Contact arrangement: <u>1</u> poles <u>1</u> throws (Details of contact arrangement are given in the assembly drawings.) 接點構成:單極單投式(詳細如組立圖所示)
- 5.Maximum ratings:最大額定:DC <u>12</u> V <u>50</u> mA
- 6.Electrical performance 電氣性能

	Property 項 目	Test conditions 試驗條件 Performance 判定基準
6.1	Contact resistance 接觸阻抗	Applying a static load twice the actuating force to the center of the stem measurements shall be made with a $\frac{1}{2}$ kHz small –current or DC5V $100$ mVcontact resistance meter. 將兩倍於動作力之靜負荷加於柄之中央以 $1$ k Hz 小電流或 DC5V $100$ mV 接觸阻抗計測定之.
6.2	Insulation resistance 絕緣阻抗	Measurements shall be made following application of DC 100V potential across terminals and across terminals and frame for one minute . 以 DC 100V 之電壓加於端子相互間及端子與外框間 1 分鐘測定之
6.3	Dielectric with standing voltage 耐電壓	AC 250V (50~60Hz) shall be applied across terminals and across terminals and frame for one minute. 以 AC 250V (50~60Hz) 之電壓加於端子相互間及端子 與外框間 1 分鐘測定之
6.4	Bounce 接點之瞬間接觸跳動時 間	Lightly striking the center of the stem at a rate encountered in normal use (3 to 4 operations per sec ) bounce shall be tested at "ON" and "OFF". 以 3~4 次/秒之正常使用速度輕輕地敲打柄之中央,開關在"開"及"關"之位置均需測定之  SWITCH
		APPD CHK DSGD TITLE:
		K C CHEN FU Chang
CVA C	DATE ADD CINE	SEP.18'2009 SEP.18'2009 SEP.18'2009 DOCUMENT NO.
SYMB	DATE APPD CHKD	DSGD   SFKHUM-001 (1/7)

SFKH	UM-001			IHUM SWIT SFNHUM 觸		TIFICATIONS 規格書		98.09.18
7 Mecha	nical performar			SITVIIOWI /與	座 八 衣 品	<b>元</b> 伯 盲		
7.IVICCHA	Property J		1 NO	Test condition	s試 驗 條	件	Perfo	ormance 判定基準
7.1	Actuating 動作力		is vertica the cente switch to 將開關之	he switch such that and then gradua or of the stem the rocome to a make s 上操作部置於垂直	at the direction of lly increasing the maximum load required shall be measured. 直方向,並在把柄量取施力期間之.	switch operation load applied to juired for the 的中央逐漸增	As sh	nowing in assembly
7.2	Trave 移動 j		Placing t is vertica force to t switch to 將開關之	he switch such that and then applying the center of the stop come to a make so 上操作部置於垂直	at the direction of ng a static load twittem the travel distributed by the measured. The man and the measured to the measured	switch operation ice the actuating ance for the	0.2:	5 +0.2 mm 5 -0.1
7.3	Return f 復歸 <i>;</i>		The samy switch op in its cen return to 將開關之	ple switch is insta peration is vertica iter the whole trav its free position s 之操作部置於垂直	lled such that the older and upon depressed distance the for	direction of sion of the stem ree of the stem to 的中央施力,使	drawi	nowing in assembly ing. 立圖上規定.
7.4	Stop stre 止動強		Placing t is vertic direction	he switch such that a static load of stem operation	switch such that the direction of switch operation a static load of 3 kgf shall be applied in the fatem operation for a period of 3 seconds. 作部置於垂直方向,並沿操作方向加3kgf 之靜負荷3秋			e shall be no sign of ge mechanically and ically. f電氣及機構上之破壞現象
7.5	Stem stre 操作部(柄)		Placing the switch such that the direction of switch operation is vertical the maximum force to withstand a pull applied opposite to the direction of stem operation shall be measured. 將開關之操作部置於垂直方向, 並在與柄之操作相反方向,施加拉力, 測量其最大抗拉力量.				500	gf.
8.Weath	ner-proof 耐候小	生能	パイエストール	4,4-,4-				
	Property J	頁 目		Test condition	s試 驗 條	件	Perfo	ormance 判定基準
8.1	Resistance temperat 耐寒性	ures	temperat for one h Drops of -30±2°C	ure for 96 hours, four, then to be mo water being taken	easured within one n away. 驗後,置於常溫常	ambient condition e hour.	同 6	7.1,7.2
8.2	Heat resis 耐熱性		Switch for temperate for one had 80±2°C 在 1 小師	or testing being ke ure for 96 hours, your, then to be mo 放置 96 小時試懸 寺內測定之	ept in the condition and in a normal a easured within one 食後,置於常溫常沒	ambient condition e hour. 堅中 1 小時,	同 6 同 7.	7.1,7.2 項 1 ,7.2 項
8.3	Moisture re 耐溼性		temperat ambient one hour 在溫度(	ure and 90~95% condition for one 50±2°C,相對溼度	RH for 96 hours.	, and in a normal measured within 6 小時試驗後,置	ohm i Insula ohm i Item Item 接觸 絕緣	ation resistance: 10 M
				APPD	CHKD	DSGD	TITL	E:
SYMB	DATE APP	D CHKD	DSGD	K C CHEN SEP.18'2009	FU SEP.18'2009	Chang SEP.18'2009		UMENT NO. SFKHUM-001 (2/7)

#### SFKHUM/SFNHUM SWITCHES SPECIFICATIONS SFKHUM-001 98.09.18 SFKHUM/SFNHUM 觸 壓 式 製 品 規 格 書 Performance 判定基準 Property 項 Test conditions 試 After 5 cycles of following conditions, the switch shall be all- Item 6 8.4 Temperature cycling owed to stand under room temperature and humidity condit-耐溫度循環試驗 Item 7.1, 7.2 ions for 1 hour and measurement shall be made within 1 hour 同6項 after that. Water drops shall be removed. 同 7.1, 7.2 項 以下記條件做5個週期的試驗後放置1小時以內測試之 但是水珠必須去除 1 cycle (1循環) +60°C -10°C 2H 1Н 9.Endurance 耐久性能 Property 項 目 Test conditions 試 驗 條 件 Performance 判定基準 9.1 Operating life Measurements shall be made following the test set forth Contact resistance: 1000 有負載壽命試驗 below: m ohm max. (1)DC 5V 5mA resistive load Insulation resistance: 10 (2)Rate of operation 2 to 3 operations per second M ohm min. (3)Depression: Upper limit of the actuating force Bounce: 20 m sec max. (4)Cycles of operation: $10 \times 10^4$ cycles Actuating force: ±30% of initial force. Item 6.3 Item 7.2 (1)DC 5V 5mA (阻抗負載) 接觸阻抗 <u>1000</u>mΩ以下 (2)動作速度:2~3 次/秒 絕緣阻抗 10 MΩ以上 (3)壓下力量:動作力之上限 接點之瞬間跳動時間 (4)動作次數: 10×10<sup>4</sup> 次 20msec 以下動作力在初期 值之±30%以內 同 6.3,7.2 項 Measurements shall be made following the set forth below: 9.2 Vibration resistance Item 6 耐振動性 쎔.Range of oscillation: 10 to 55 Hz Item 7.1, 7.2 웹.Amplitude pk-to-pk : 1.5 mm 씻.Cycle of sweep : 10-55-10 Hz in one minute approx. 同6項 同 7.1.7.2 項 엥.Mode of sweep: Logarithmic sweep or uniform sweep. 셔.Direction of oscillation: Three mutually perpendicular directions including the direction of stem travel. 역.Duration of testing: 2 hours each for a total of 6 hours थ.振動數範圍: 10~55 Hz 렙.全振幅:1.5 mm 쎛.掃瞄週期:10-55-10 Hz 約 1 分鐘 **炒.掃瞄振動之變化方式:近似對數或直線** 从.振幅方向:相互垂直之三個方向(含柄移動之方向) **ዻ.試驗時間:各2小時(計6小時) APPD** CHK **DSGD** TITLE: K C CHEN FU Chang DOCUMENT NO. SEP.18'2009 SEP.18'2009 SEP.18'2009 SFKHUM-001 (3/7)APPD CHKD DSGD YMB DATE


#### SFKHUM/SFNHUM SWITCHES SPECIFICATIONS SFKHUM-001 98.09.18 SFKHUM/SFNHUM 觸壓式製品規格書 Performance 判定基準 Property 項 Test conditions 試 Impact shock resistance Measurements shall be made following the test set forth 9.3 Item 6 below: 耐衝擊性 Item 7.1, 7.2 (1)Acceleration: 80g 同6項 (2) Cycle of test: 3 cycles a total of 18 cycle. 同 7.1,7.2 項 (1)用 80g 加速度 (2)沿圖示 6 個方向, 每方向 3 次共 18 次.

◆◆◆Switch Handling Precaution ◆◆◆◆◆使用上應注意事項

1. Reflow Soldering condition.

Reflow 焊錫條件

Temperature 溫度(°C)



### Time(時間) ----- Temperature profile (溫度圖)

### Caution 注意事項

- (1).The condition mentioned above is the temperature on the P.C board surface on which parts are mounted. There are cases where board's temperature greatly differs from switch's surface temperature. depending on the board's material, size, thickness, etc. Care, therefore, should be taken to prevent the switch's surface temperature from exceeding 260°C. 上述條件為 P.C.B 組裝表面溫度,部份基板因材質,大小及厚度等引起基板溫度與 SW 表面溫度很大差異, SW 表面溫度勿超過 260°C 請確認
- (2). As the conditions vary some how depending on the kind of reflow soldering equipment, please make sure you have the right one before use.
  - 因 REFLOW 爐的種類不同,條件設定上亦有所差異,使用前詳加確認.
- 2.Other precautions 其它注意事項
  - (1). Following the soldering process do not try to clean the switch with a solvent or the like. 在焊錫過程中, 不可用溶劑或類似品清洗開關.
  - (2).Safeguard the switch assembly against flux penetration from its top side. 焊錫時請注意防止助焊劑從開關頂部滲入.
  - (3).Please have the products keep in close status and the storage time is 90 days guaranty agter delivering the goods at most. 為了避免保管場所的環境引起端子變色,未到使用之前,請勿拆封.TACT SW 的保存期限出貨後 3 個月內
  - (4)Please understand that the specifications other then electric and mechanical characteristics and outside dimensions may be changed at our own discretion.

					APPD	СНК	DSGD	TITLE:	
					K C CHEN	FU	Chang	DOCKIN AENTENIO	
					SEP.18'2009	SEP.18'2009	SEP.18'2009	DOCUMENT NO.	(4/7)
SYMB	DATE	APPD	CHKD	DSGD				SFKHUM-001	(4/7)

## SFKHUM/SFNHUM SWITCHES SPECIFICATIONS SFKHUM/SFNHUM 觸 壓 式 製 品 規 格 書

98.09.18

### 10.其它 Others

쎔.When chip components is soldered on the back side of P.C.B by DIP soldering, after switch soldered by reflow soldering, flux will possibly creep up at the exterior wall of the housing and penetrate into the housing due to flux ejection


Therefore, When the P.C.B is designed, please do not locate through holes adjacent to the switch mounted area. P.C.B 設計時貫穿孔位置請勿鄰近於此開闢固定位置,以避免助焊劑噴流滲入開闢造成不良.

웹.When this switch is mounted by the chip, it can be dispositioned because the body turns on the way to the P.C.B if you Vacuum the top side of the stem.

Therefore we recommend that the stem should be vacuumed by the called "escape part the frame".

本開關如以 CHIP MOUNT 機器自動裝著時,如由把柄先端直接吸取至基板裝著過程中,可能由 SW 本體旋轉而發生黏著偏移,建議吸嘴部逃孔大於把柄外徑後真空吸取確保黏著精度.

### Example which dose a switch in the vacuum. 真空吸取範例



					APPD	СНК	DSGD	TITLE:	
					K C CHEN	FU	Chang	DOCUMENT NO.	
SYMB	DATE	APPD	CHKD	DSGD	SEP.18'2009	SEP.18'2009	SEP.18'2009	SFKHUM-001	(5/7)

## SFKHUM/SFNHUM SWITCHES SPECIFICATIONS SFKHUM/SFNHUM 觸 壓 式 製 品 規 格 書

98.09.18

1.Scope 適用範圍

This specification covers the requirements of the taping packaging for SFKHMM standard type of TACT switches. 本規範適用於 TACT switches SFKHMM 之承載帶包裝方式.


2.Packaging Materials 包裝材料

Item 項目	Material 材料
Package 包裝箱	Cartons.
Reel 捲盤	Antistatic Polystyrene.
Carrier Tape 承載帶	Conductive Polystyrene.
Cover Tape 封口帶	Polyster heat active.

- 3.Aging Quantity 包裝數量
- 3.1.The number of the reels. 捲盤數量

Fourteen(14)reels at maximum, which contain 21,000 switches, shall be packed in a package. 每個包裝箱可裝 14 捲, 計 21,000 個開關.


- 3.2. The number of the switches. 開關數量
  - 1,500 switches shall be packed in a reel. 每捲包裝數量 1,500 個.
- 4.Carrier Tape Form and Dimensions 承載帶形狀及尺寸



# SFKHUM/SFNHUM SWITCHES SPECIFICATIONS SFKHUM/SFNHUM 觸 壓 式 製 品 規 格 書

93.08.06

5.Reel Form and Dimensions 捲盤形狀及尺寸



(mm)

#### 6.Packaging Procedure 包裝方式

- 6.1.At the beginning of reeling, the end of the tape,200mm or more, shall be empty and fit into the groove in the reel core. 料捲起點約 200 mm (或更多)承載帶須空出並固定於蕊心.
- 6.2.After reeling , the end of the tape  $130 \pm 4$ mm, shall be empty and the tape edge shall be cut in  $45^{\circ}$ .

料捲終點承載帶須空出約 130±4mm 尾端並裁成 45°角.

The cover tape shall be extended  $250 \pm 10$  mm from the tape edge and fixed with tape.

封口帶須從承載帶終點延伸約 250±10 mm 並與承載帶固定.

- 6.3. Total number of missing switches shall be less than 3 in one reel.
  - 每捲漏裝數不可超過 3PCS.
- 7.Storage Condition 保存狀態
  - 7.1.Storage Environment 儲存環境

-20 to 50℃, 20 to 85%RH. 溫度-20~50℃,溼度 20~85%RH.

(Storage in high temperature and high humidity shall be avoided).

(儲存時避免放置於高濕高溫下).

					APPD	СНК	DSGD	TITLE:	
					K C CHEN	FU SEP 1822000	Chang	DOCUMENT NO.	
SYMB	DATE	APPD	CHKD	DSGD	SEP.18'2009	SEP.18'2009	SEP.18'2009	SFKHUM-001	(7/7)

